TITLE OF THE INVENTION

DATA PROCESSING SYSTEM, DATA PROCESSING APPARATUS AND DATA PROCESSING METHOD

5 ## BACKGROUND OF THE INVENTION

1.   Field of the Invention

The present invention relates to a data processing system, a data processing apparatus and a data processing method, and, in particular, to a

10 data processing system, a data processing apparatus and a data processing method for mainly processing a data stream such as moving picture data or so.

2.   Description of the Related Art

15 Recently, digital signal processing technology has made remarkable progress, and, along therewith, development has been proceeded with worldwide for a system achieving digital broadcast, and fusion between broadcast and communications. In

20 this term, the most essential technology is a technology of compressing video/audio data. As the compression technology, for example, a coding compression method standardized in MPEG (Moving Picture Experts Group) exists. For this coding

25 compression method, study has been proceeded with for achieving worldwide technical standardization of broadcast, communications and storage media.

Further, recently, an image dispatch service has been developed with a use of various

30 types of wide-area communication networks such as the Internet, and so forth. In many cases, such an image dispatch service applies a stream dispatch method utilizing the above-mentioned MPEG standard. For achieving such data dispatch handling a large

35 size of data such as image data, the communication network applied should have a transmission band providing a large communication capacity. However,

in general, as the infrastructure is limited with respect to the increasing demand for the communications, a transmission band providing a sufficient communication capacity cannot be prepared

5   in some case. Furthermore, a common communication network is made by various types of transmission channels of various transmission bands such as a LAN, an SDH, an ISDN, a public circuit, and so forth. In such a various types of communication networks, in

10   some case, different transmission bands are included in a transmission path from an information transmission source through a transmission destination.

In such a situation, in case a

15   transmission band applied is narrower than a coded rate of information coded in the information transmission source, real-time video reproduction may not be provided at the transmission destination. In such a case, at the transmission destination,

20   video reproduction can be started after all the MPEG steam has been completely received, and thus, the real-time feature of the video data is remarkably degraded. Furthermore, in such a case, the receiving processing should not be interrupted until

25   the entire MPEG stream has been received. As a result, the transmission destination may be needed to receive even a part of video data which is not actually required. Furthermore, in case where there are a plurality of transmission sources, and a user

30   selects a desired transmission source therefrom, some inconvenient situation for the user may occur if it is necessary to receive all the data stream before reproducing it as mentioned above.

Japanese laid-open patent application No.

35   S64-57887 discloses a method in which a process is repeated in each of which data is received and stored for a predetermined time interval and

reproduction is performed on each of the thus-stored parts of data. However, in this method, video reproduction is interrupted frequently, and thus, a sufficiently high image quality may not be secured.

In a case where MPEG stream dispatch is performed in such a system, a transcoder is inserted between the transmission source apparatus and the transmission destination apparatus, in some case. The transcoder is applied for converting a bit rate of a data stream appropriately according to a data transmission band of a communication channel applied for transmission of the data stream. In other words, in case where a digital signal of video/audio which is coded and compressed is transferred through transmission media having different bit rates, bit rate conversion is performed appropriately according to the bit rates of the respective particular transmission media.

Conventionally, a stream which is compressed and coded according to the MPEG standard is received by the above-mentioned transcoder apparatus, which once decodes the stream into an original image signal or so, and, after that, encodes and compresses again the thus-obtained image signal or so according to the MPEG standard according to a bit rate applied for the transmission destination apparatus. Then, after that, data transmission is performed at the bit rate suitable to the transmission band for the transmission destination. However, in such a method, at the transmission destination, the received data is again decoded so as to return to the original image signal or so before reproducing it. Accordingly, for the data stream, MPEG coding/decoding processing is respectively performed, and thus, the video quality may be remarkably degraded.

Japanese laid-open patent application No.

H11-177986 discloses another method for transmitting from a wide band network through a narrow band network, in which only I pictures are transmitted. This method is a method in which only I pictures

5   from among I pictures (intra-frame coded images), P pictures (inter-frame forward-directional predictive coded images) and B pictures (both-directional predictive coded images) according to the MPEG standard, are extracted, and then, are transmitted

10   through the narrow band network. According to this method, only the I pictures, for which decoding can be made independently and having a high image quality, in comparison to the P and B pictures, are transmitted, without transmitting the P and B

15   pictures, and thus, transmission capacity required can be effectively reduced. However, in this method, the pictures other than the I pictures are discarded.

For example, in a technical field of a moving picture dispatch in a network of monitoring

20   system monitoring through the network for a predetermined event, which field has been being developed recently, if the conventional method is applied in which encoding is performed again according to a band width of a narrow band network

25   applied, the image quality may be degraded as mentioned above since high rate image compression is performed. On the other hand, in case of applying the above-mentioned method of transmitting only the I pictures, the frames reproduced from themselves

30   have a high image quality. However, in this case, as the P and B picture frames are thinned out as mentioned above, the images actually reproduced include only intermittent ones from the I pictures as a result, and, thus, there is a possibility that

35   some important frames in terms of a predetermined monitoring purpose may be omitted. For example, in case of traffic accident monitoring system, a frame

of a moment in which a traffic accident actually occurred, a frame clearly showing a number plate of a escaping vehicle, or so, may be omitted, or, in case of shop/store anticrime monitoring system, a frame of a just moment in which a criminal person committed a crime may be omitted, or so. In case of a moving picture dispatch processing system applied to such a monitoring system for which omission of frames is not permitted, it is demanded that each frame has a high image quality, frame thinning out is not performed, and also, at a reception end, frame reproduction may be performed in a real-time manner to the utmost extent.

Thus, in case of performing data dispatch after converting a bit rate according to an available band in an MPEG stream dispatch system employing a transcoder with a user of a network having a limited available band, information finally transmitted from a transmission source is reduced before being reproduced at a transmission destination any case in which a spatial compression in which image resolution or image quality is reduced, or a temporal compression in which the number of frames is reduced for unit time interval while remaining frames are reproduced at high image quality, in other words, frames are thinned out is applied there.

SUMMARY OF THE INVENTION

The present invention has been devised in consideration of the above-mentioned situation, ands an object of the present invention is to provide a data transmission processing system by which, when a data stream is transferred with a use of an insufficient information transmission band, the information of the data stream is not reduced, and also, reproduction can be performed at a transfer

destination with a real-time feature to the utmost extent.

In order to achieve the object of the present invention, according to the present invention, time information of a data stream is updated according to a conversion of a data transfer rate, and, upon decoding the transfer-rate-converted data stream, decoding is performed according to the time information which is thus updated. By applying this manner, even arrival of data at a transfer destination is delayed due to a reduction in an available data transfer capacity, the time information of the data is previously extended (updated) as mentioned above with an anticipation of such an arrival delay. Thereby, as long as decoding is performed according to the time information which is thus extended, it is possible to avoid mismatch winch otherwise would occur between time progress according to a reference clock signal in a decoding apparatus at the destination end and the time information of the relevant data to be decoded therewith.

Specifically, in case of transmitting an MPEG stream or so from a wide band network into a narrow band network, time information which the MPEG stream has is changed according to the constriction rate in the transmission band of the applied network for example. Thereby, it is possible to dispatch the contents of video stream with a high image quality at a reduced delay (without waiting for the completion of reception of the entire data even having a large size). Furthermore, as the bit rate conversion is performed without thinning out of any frames, it is possible to provide an actual display of the video contents at a receiving apparatus simultaneously with a transmission start time at a transmission apparatus even through a narrow band

network. As a result, it is possible to receive all the frames which are transmitted without fail, and then, to positively reproduce a video display thereof.

5   According to the present invention, the time information of transfer data is updated to be extended according to a reduction rate in a data transfer rate which is limited according to an available transmission band/capacity of a data

10   transmission path. Thereby, in a data transfer destination, as long as the received data is processed according to the thus-updated time information, it is possible to always execute predetermined data processing such as decoding and

15   reproduction properly.

Especially in a case where a data stream such as video data is processed, video has a characteristic such that a human being viewer can figure out the information contents properly even if

20   a reproduction rate is slowed down as long as reproduction is performed without thinning out of any frames of the video data. By utilizing this characteristic, according to the present invention, data dispatch is performed after the time

25   information of the data stream is appropriately extended or shifted forward and thus updated. Thereby, at the receiving end, by executing even a common manner of decoding and reproduction processing, it is possible to achieve reproduction

30   of moving pictures immediately after it is received as long as the reproduction is performed according to the thus-updated time information.

BRIEF DESCRIPTION OF DRAWINGS

35   Other objects and further features of the present invention will become more apparent from the following detailed description when read in

conjunction with the accompanying drawings:

FIG. 1 shows a system configuration of each embodiment of the present invention;

FIG. 2 shows a block diagram of an MPEG encoder shown in FIG. 1;

FIG. 3 shows a block diagram of an MPEG transcoder shown in FIG. 1;

FIG. 4 shows a block diagram of an MPEG decoder shown in FIG. 1;

FIG. 5 shows an operation flow chart of a reception sequence in the transcoder shown in FIG. 3;

FIG. 6 shows an operation flow chart of a transmission sequence in the transcoder shown in FIG. 3;

FIG. 7 shows an operation flow chart of a time information updating sequence in the transcoder shown in FIG. 3;

FIG. 8 shows an operation flow chart of a picture deletion sequence in the transcoder shown in FIG. 3;

FIG. 9 shows an operation flow chart of a receiving sequence in the decoder shown in FIG. 4;

FIGS. 10, 11, 12, 13, 14 and 15 illustrate a data stream format in a data stream according to MPEG 2;

FIGS. 16 and 17 illustrate numerical example in updating of time information in an MPEG steam according to each embodiment of the present invention; and

FIG. 18 illustrates change in reproduction rate according to updating of time information in an MPEG steam according to each embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

An outline of a first embodiment of the

present invention will now be described. First, a data structure of an MPEG stream will now be described. An MPEG system integrates a coded stream such as MPEG video data, MPEG audio data or so

5   including synchronization information (or time information) therefor. With regard to the MPEG system, FIGS. 10, 11, 12, 13, 14 and 15 illustrate syntaxes of the data format of an MPEG 2 stream according to the recommendation H.222.0, which is a

10 standard book for the MPEG 2.

As shown, the MPEG system includes a higher layer (pack layer) and a lower layer (packet layer). The pack layer includes pack headers (FIG. 12 shows a syntax of the pack header), and, in the

15 pack layer, system headers (FIG. 13 shows a syntax of the system header) and packets (FIG. 14 shows a syntax of the PES packet) are included.

In the MPEG stream, for the purpose of synchronization at a time of reproduction thereof, a

20 time reference value SCR (System Clock Reference; ① in FIG. 12) is set in the pack header. In each packet, time management information PTS (Presentation Time Stamp; ② in FIG. 15) for reproduction output and time management information

25 DTS (Decoding Time Stamp; ③ in FIG. 15) for decoding are set. A decoding apparatus which receives the MPEG stream has a synchronization signal (referred to as 'SystemClock', hereinafter) as time reference, sets the value of SCR of the

30, received stream in the SystemClock, and therewith, the SystemClock is calibrated appropriately.

The above-mentioned DTS and PTS are set for each decoding and reproduction unit (each frame for video data; and each audio frame for audio data).

35 By a predetermined 'PTS & DTS flag', it is determined whether or not a relevant packet has a PTS/DTS. In a decoder or decoding apparatus, when

the SystemClock has a value of DTS of the packet,
decoding of the packet is executed, and, when the
SystemClock has a value of PTS of the packet, the
packet is reproduced. As a result, synchronization
5   with a coding end (apparatus) and synchronization
between audio data and video data are achieved.

       For example, left-hand tables in FIGS. 16
and 17 show numerical examples of common SCR, PTS
and DTS set in an MPEG stream. In each table, the
10· top correspond to the initial part of the stream,
and, lower subsequent parts of the table correspond
to subsequent parts of the stream, respectively, in
sequence. As the value of the first SCR in this
case is 666 msec., and at this time, the SystemClock
15   is thus set as 666 msec. After that, the
SystemClock is updated according to the progress of
the actual time with reference to the time 666 msec.
Then, when the time indicated by the SystemClock
reaches 872 msec., video frame data included in a
20   PES packet having the same value 872 msec. in Video
PTS/DTS, shown in FIG. 16, is decoded and reproduced.
After that, the SystemClock is updated similarly,
and then, when the SystemClock has the time value of
906 msec., a subsequent relevant image frame, shown,
25   is decoded and reproduced. Similarly, after that,
according to the progress in the time value of the
SystemClock, corresponding image frames are decoded
and reproduced, in sequence.

       It is assumed that the entire MPEG stream
30   received by a transcoder is then dispatched through
a narrow band network. In this case, if the given
MPEG stream is transmitted through the narrow band
network as it is, as the data transfer rate is
reduced with respect to the band constriction rate,
35   times at which respective image frames arrive at a
transmission destination are accordingly delayed one
by one gradually. As a result, in the transmission

destination decoder apparatus, mismatch occurs
between the above-mentioned SystemClock and the
values in SCR/PTS/DTS of the received stream. As a
result, proper decoding processing may not be
5   achieved due to the above-mentioned mismatch.

That is, in the example shown in FIG. 16,
left-hand table, when the stream is received first,
the SystemClock is set as 666 msec. which is the
value of SCR. After that, the first image frame
10   having the PTS/DTS value of 872 msec. is received
and reproduced when the SystemClock has the same
value. After that, it is assumed that the arrival
of the subsequent frame data is delayed as mentioned
above due to the narrower band. In this case, a
15   situation may occur in which, even when the
SystemClock then has the value of 906 msec., the
image frame data having the same value in PTS/DTS
has not yet arrived at this decoder. In this case,
mismatch occurs between the PTS/DTS value of the
20   data which has already arrived and thus can be
processed and the current value in the SystemClock.
In order to avoid such mismatch which occurs between
the SystemClock and the value in SCR, PTS and DTS
during decoding and reproduction, a countermeasure
25   should be taken in which, for example, the entire
stream is once received, and stored, and after that,
decoding and reproduction of the stored data are
started. Thus, the real-time feature upon decoding
and reproduction of dispatched data is remarkably
30   degraded.

According to the first embodiment of the
present invention, in order to solve this problem,
in a transcoder which dispatches a stream through a
narrow band network, the values in the SCR/PTS/DTS
35   of the stream are previously updated into delayed
time values suitable for a decoder which then
receives this stream through the narrow band network,

and decodes and reproduces it.   By applying this
scheme, in the decoder, after receiving the stream
through the narrow band network, the received
video/audio data can be immediately reproduced in
5   timing according to the thus-updated SCR/PTS/DTS
frame by frame.

FIG. 1 shows a block diagram illustrating
a system configuration of an MPEG stream dispatch
system employing an MPEG decoder in the first
10   embodiment of the present invention.   In this system,
as communication networks applied, a wide band
network NW1 of 6 Mbps and a narrow band network NW2
of 2 Mbps are assumed.   To the wide band network NW1,
an MPEG encoder 10 which dispatches an MPEG stream
15   in a live manner, an MPEG transcoder 20 which once
receives the stream from the MPEG encoder 10 and
then dispatches it through the narrow band network
NW2, an MPEG decoder 60 and a client 200 which
receive/decode/reproduce the stream received from
20   the MPEG encoder 10, and a server 100 which performs
control and setting of coding modes, live dispatch
addresses, and so forth for the MPEG encoder 10, the
MPEG transcoder 20, or so, are connected.

To the narrow band network NW2, the above-
25   mentioned MPEG transcoder 20 which receives the
stream from the MPEG encoder 10 connected to the
wide band network NW1, and dispatches it then
through the narrow and network NW2, and an MPEG
decoder 40 and a client 300 which
30   receive/decode/reproduce the stream from the MPEG
transcoder 20 through the narrow band network, are
connected.

In this system, the server 100 controls
all the apparatuses connected to the wide band
35   network NW1.   In other words, it sets a coding mode
(MPEG 1/2/4, coding bit rate, designating whether or
not audio is included, or so), a live dispatch

address or so, for the MPEG encoder 10. Further,
for the MPEG transcoder 20, the server 100 sets a
live receiving address, a live dispatch address with
which a received MPEG stream is then dispatched
5   through the narrow band network NW2. Furthermore,
the server 100 sets a live receiving address for the
MPEG decoder 60, the client 200, or so.
         The MPEG encoder 10 is located at a place
at which the server 100 can monitor it, encodes
10   input video data in a set coding mode, and
dispatches the thus-obtained MPEG stream to an
address set by the server 100. The MPEG transcoder
20, the MPEG decoder 60 and the client 200 is
installed at an office or a monitoring center. The
15   MPEG transcoder 20 has at least two types of network
interfaces, performs data conversion on an MPEG
stream received through the wide band network NW1,
and dispatches it then through the narrow band
network NW2. In the MPEG decoder 20 or the client
20   200, by decoding and reproducing a received MPEG
stream, monitoring for a predetermined event
occurring at a remote location can be executed.
         Each of the MPEG decoder 40 and the client
300 connected to the narrow band network NW2 is
25   installed in a headquarter office, a satellite
office, a home of a user, or so. Setting of the
live receiving addresses for these apparatuses (i.e.,
live dispatch addresses in the MPEG transcoder 20)
is performed by each client terminal 200.
30   Furthermore, in the MPEG decoder 40 or the client
200, by decoding and reproducing a received MPEG
stream, monitoring with a use of monitoring video
transmitted from the encoder 10 of so through the
wide band network NW1 can be achieved by a
35   predetermined watch person.
         Thus, it is assumed that the moving
picture dispatch system according to the first

embodiment of the present invention is applied to a
monitoring system in which a possible predetermined
event is pick up by a TV camera or so, not shown,
and video data thus obtained is used for the
5 monitoring work. In this monitoring system, a
specific event, such as a traffic accident on a road,
an illegal intruder in a shop/store, a siren sound
or so, is detected by a predetermined detecting
system, not shown, for example, an image sensor, a
10 voice sensor, a millimeter-wave sensor, or so,
installed in a location which should be managed,
thus, event occurrence information is generated
therewith, and the information is provided to the
encoder 10 in a form of a monitoring signal.
15 Simultaneously, video data or audio data taken by a
video camera, not shown, is taken in a real-time
manner, and is provided to the encoder 10 also in a
form of a monitoring signal.
         In the present embodiment, as the wide
20 band network NW1, an IP network of 100 Base-T or 10
Base-T, or so, is assumed, while, as the narrow band
network NW2, a radio LAN, an ISDN circuit, a PHS
circuit or so, is assumed, for example.
         FIG. 2 shows a block diagram of the above-
25 mentioned MPEG encoder 10. This MPEG encoder 10
includes a video A/D converter 11 performing analog-
to-digital conversion on input video, an audio A/D
converter 12 performing analog-to-digital conversion
on input audio, an MPEG coding part 13 performing
30 MPEG coding on an input digital video/audio signal,
an MPEG stream dispatch part 16 dispatches in a
real-time manner a coded MPEG stream through the
network, an even occurrence information transmitting
part 17 receives a signal reporting that some event
35 has occurred externally and dispatches it through
the network NW1, a server IF part 14 accepting a
setting request from a server 100 or a stored image

acquisition request, and a setting control part 15
which controls, according to a setting request by
the server 100, the MPEG coding part 13, MPEG stream
dispatch part 16 and event occurrence information
5   transmitting part 17.

As to initial device setting of the MPEG
encoder 10, the server IF part 14 receives a coding
mode, a live dispatch address or so from the server
100, the setting control part 15 interprets it, sets
10   the coding mode in the MPEG coding part 13, and sets
the live dispatch address in the MPEG stream
dispatch part 16. After that, video/audio data
provided externally as mentioned above is converted
into a digital signal via the respective one of the
15   A/D converters 11 and 12, and then, the MPEG coding
part 13 performs coding thereon with the coding mode
set by the server as mentioned above. The thus-
obtained coded MPEG stream is dispatched in a real-
time manner through the network NW1. Further, in
20   case a signal as event occurrence information is
provided externally as mentioned above and is
received, the information is dispatched through the
network NW1 from the event occurrence information
transmitting part 17.
25   FIG. 3 shows a block diagram of the MPEG
transcoder 20 mentioned above. This transcoder 20
includes an MPEG stream receiving part 28 receiving
in a real-time manner an MPEG stream from the MPEG
encoder 10, an MPEG decoding part 29 decoding the
30   received MPEG stream, a video D/A converter 30
converting the decoded digital video data into
analog video data, an audio D/A converter 31
converting the decoded digital audio data into
analog audio data, a selecting switch 32 for
35   selecting as to whether or not the received MPEG
stream is dispatched through the narrow band network
NW2, a MPEG stream buffer 33 once storing the

received MPEG stream, a stream buffer writing part
26 writing the received MPEG stream into the MPEG
stream buffer 33, a stream buffer reading part 25
reading out the MPEG stream once stored in the MPEG
5   stream buffer 33, a time information updating part
34 updating the time information of the MPEG stream
by a manner as will be described later, an MPEG
stream dispatch part 23 dispatching the MPEG stream
read out from the MPEG stream buffer 33 through the
10   narrow band network NW2, an event occurrence
information receiving part 27 receiving the event
occurrence information from the MPEG encoder 10, a
request receiving part 24 accepting a time request
from the MPEG decoder 40 for the MPEG stream to be
15   sent out as will be described later, a server IF
part 21 accepting a setting request from the server
100, and a setting control part 22 which controls
the MPEG stream receiving part 22 and the MPEG
stream dispatch part 23 according to a setting
20   request given by the server 100.

       Initial device setting of the transcoder
20 is performed as follows: Live dispatch
address/live receiving address received from the
server 100 are interpreted by the setting and
25   control part 22, and these addresses are then set in
the MPEG stream dispatch part 23 and the MPEG stream
receiving part 28, respectively. After that, the
MPEG stream received by the MPEG stream receiving
part 28 is decoded by the MPEG decoding part 29
30   according to the MPEG standard, and then, reproduced
into video or audio information in a visible or
audible state through the video and audio D/A
converters 30 and 31.

       On the other hand, when the event
35   occurrence information receiving part 27 receives
even occurrence information from the MPEG encoder 10,
and thus, it is recognized that some event has

occurred, the selecting switch 32 is turned, and thus, the received MPEG stream is written into the MPEG stream buffer 33 by the stream buffer writing part 26. The stream buffer reading part 25 reads
5 out the MPEG stream from the MPEG stream buffer 33, and the time information thereof is updated as is necessary by the time information updating part 34, and then, the MPEG stream is dispatched through the narrow band network NW2 by the MPEG stream
10 dispatched part 23. Thus, dispatched of the MPEG stream is executed.

FIG. 4 shows the above-mentioned MPEG decoder 40. The MPEG decoder 40 includes an MPEG stream receiving part 47 receiving in a real-time
15 manner an MPEG stream from the MPEG transcoder 20, an MPEG decoding part 48 decoding according to the MPEG standard the received MPEG stream, a video D/A converter 49 converting the thus-decoded digital video data into analog video data, an audio D/A
20 converter 50 converting the thus-decoded digital audio data into analog audio data, an MPEG stream buffer 44 storing the received MPEG stream, a stream buffer writing part 46 writing the received MPEG stream into the MPEG stream buffer 44, a stream
25 buffer reading part 45 reading out the MPEG stream from the MPEG stream buffer 44, a time information updating part 52 updating the time information of the MPEG stream in a manner which will be described later, a selecting switch 51 for selecting which one
30 of the MPEG stream which is currently received and the MPEG stream which is already stored in the MPEG stream buffer 33 is to be decoded, a request transmitting part 43 issuing a time request to the MPEG transcoder for the MPEG stream to be brought
35 therefrom, a user IF part 41 accepting a setting request from a user, and a setting control part 42 controlling according to the setting request given

by the user the MPEG receiving part 47 and the
selecting switch 51 accordingly.

Initial device setting of the above-
described decoder is performed as follows: A live
5   receiving address designated by the user is
interpreted by the setting and control part 42, and
is set in the MPEG stream receiving part 47. A MPEG
stream received by the MPEG stream receiving part 47
is decoded according to the MPEG standard by the
10   MPEG decoding part 48, and is reproduced into
visible or audible information through the video or
audio D/A converter 49 or 50. On the other hand,
the received MPEG stream is written into the MPEG
stream buffer 44 by the stream buffer writing part
15   46. The thus-stored received MPEG stream can be
decoded by the MPEG decoding part according to the
MPEG standard in response to the user's request, and
reproduced into visible or audible information
through the video or audio D/A converter 49 or 50.
20   The first embodiment of the present
invention having the above-described configuration
will now be described in detail.

According to the present embodiment, a
high rate coded MPEG stream dispatched through the
25   wide band network NW1 from the MPEG encoder 10 is
further dispatched by the MPEG transcoder 20 through
then the narrow band network NW2. Thus, through the
narrow band network NW2, the thus-dispatched MPEG
stream is received by the MPEG decoder 40, and after
30   that, quick reproduction as quickly as possible can
be achieved.

It is assumed that the MPEG encoder 10
connected to the wide band network NW1 continues to
dispatch an MPEG stream encoded according to the
35   coding mode designated by the server 100 through the
wide band network NW1. Further, when event
occurrence information is input externally, the

event occurrence information is dispatched through
the wide band network NW1 from the event occurrence
information transmitting part 17. As a transmission
format applied for transmitting the event occurrence
5   information, any type of one can be applied as long
as the dispatched information can be properly
received and interpreted by the reception end.

FIG. 5 shows a sequence at a time of
receiving in the transcoder 20, FIG. 6 shows a
10   sequence at a time of transmission in the transcoder
20, and FIG. 7 shows a sequence at a time of time
information updating. With reference to these
figures, a function of dispatch operation in the
transcoder 20 will be described. In the present
15   embodiment, it is assumed that an MPEG stream only
including video data is dispatched to the MPEG
transcoder 20 through the wide band network NW1.

First, receiving processing in the
transcoder 20 will now be described with reference
20   to FIG. 5. First, in Step S1, an MPEG stream
dispatched through the wide band network NW1 is
received in a packet unit or in a frame unit.
Simultaneously, event occurrence information is
received through the wide band network NW1 in Step
25   S2. When it is recognized therefrom that some event
has occurred, the received packet/frame of MPEG
stream is stored in the MPEG stream buffer 33 in
Steps S4, S5 and S6. In this example, it is assumed
that no audio data exists in the received MPEG
30   stream as mentioned above. Accordingly, the
received MPEG stream is written into a video buffer
part of the MPEG stream buffer 33, in Step S6.
Furthermore, commonly, it is assumed that the MPEG
transcoder 20 is installed at a location such as a
35   video monitoring center or so. In such a case, the
received MPEG stream is decoded according to the
MPEG standard by the MPEG decoding part 29, and then,

is reproduced from a TV monitor or so through video/audio D/A converters 30 and 31.

Transmission processing in the transcoder 20 will now be described with reference to FIG. 6. The transmission processing is executed independently from the above-described receiving processing. First, in case no even occurs (No in Step S11), no operation is performed. When an event occurs (Yes), it is determined whether or not audio data is stored in an audio buffer part of the MPEG stream buffer 33 in Step S12. In this example, it is assumed that no audio data exits, and thus, no audio data is stored (No in Step S12). Accordingly, data reading is performed only from the video buffer part of the MPEG stream buffer 33 in Step S14. In the video buffer part in the MPEG stream buffer 33, system information such as a system header or video data is stored.

In the MPEG stream, the time information such as the above-mentioned time reference value SCR, time management information for reproduction PTS, and time management information for decoding DTS are set. If these time information are dispatched as they are through the narrow band network NW2, as the data rate is reduced according to the band constriction rate accordingly, data transfer delay occurs as mentioned above. As a result, the MPEG stream cannot be received by the MPEG decoder 40 in prescribed timing, thus, as mentioned above, mismatch occurs between these time information and the SystemClock in the decoding end (apparatus), and as a result, proper reproduction may not be achieved. In order to solve this issue, in the MPEG transcoder 20 in the embodiment of the present invention, the above-mentioned time information is updated before the MPEG stream is dispatched through the narrow band network NW2 to the decoder 40.

The time information updating processing in the transcoder 20 will now be described with reference to FIG. 7. First, it is determined in Steps S21 and S22 whether data read out from the

5 MPEG stream buffer 33 is a pack header, a system header or a video packet. In this case, it is assumed that the MPEG stream buffer 33 does not store therein audio packets. When the determination result is a packet header (Yes in Step S21), the

10 first SCR occurring after the above-mentioned specific event occurs is stored. That is, the first SCR after the event occurs is stored as "SCR_I" in Step S25. In the other case (No in Step S24), the SCR value read out from the MPEG buffer 33 is stored

15 as "SCR_B".

Next, in Step S26, updating of SCR is performed by the time information updating part 34. It is assumed that the coded rate in the MPEG stream coded by the MPEG encoder 10 is "$RATE_B$", while the

20 available circuit transfer rate in the narrow band network NW2 is assumed as "$RATE_N$". Then, the SCR value in the MPEG stream to be dispatched through the narrow band network NW2 is replaced by the value obtained from the following formula:

25

$$SCR_I + ((SCR_B - SCR_I) \times (RATE_B/RATE_N))$$

That is, the time information SCR is extended or delayed by the amount corresponding to the ratio

30 between the data rate in the coded stream and the available data transfer rate in the narrow band network NW2. In the example of FIG. 16, $RATE_B/RATE_N$ = 3. This corresponds to triple band constriction. In the packet on the line 2 of the table in FIG. 16,

35 SCR_B = 684 msec. with respect to SCR_i = 666 msec. Accordingly, the above-mentioned formula becomes:

$$666 + ((684 - 666) \times 3) = 720 \ (msec.)$$

Thus, the value after tripling conversion shown in the right-hand table in FIG. 16 is obtained.

Similarly, in case where the received data is a video packet (No in Step S22), assuming that the PTS value read out from the MPEG stream buffer 33 is PTS_B and the DTS value is DTS_B therefor, the time information updating part 34 replaces the PTS value and the DTS value in the MPEG stream to be dispatched through the narrow band network NW2 with the values obtained from the following formulas in Step S23:

$$SCR_I + ((PTS_B - SCR_I) \times (RATE_B/RATE_N))$$

$$SCR_I + ((DTS_B - SCR_I) \times (RATE_B/RATE_N))$$

That is, each of the time information PTS and DTS is extended or delayed respectively by the amount corresponding to the ratio of the data rate in the coded stream with respect to the available data transfer rate in the narrow band network NW2. In the packet on the line 9 of the table in FIG. 16, $PTS_B = DTS_B = 906$ msec. with respect to $SCR_i = 666$ msec. Accordingly, each of the above-mentioned formulas becomes:

$$666 + ((906 - 666) \times 3) = 1386 \ (msec.)$$

Thus, the value after the tripling conversion shown in the right-hand table in FIG. 16 is obtained.

By repeating the processing (the loop of Steps S21 through S27), the time information in the relevant MPEG stream is updated in sequence, and as a result, the time information (time stamps) after the conversion (in the right-hand table in FIGS. 16

and 17) is obtained, for example. In the present
embodiment, the time information in the respective
headers and packets are updated according to the
band constriction rate appropriately. Thereby, even
5 in a case where the data arrival time at the
transmission destination is delayed as a result of
the reduction in the data transfer rate according to
the band constriction, the data positively arrives
at the transmission destination at the respective
10 designated time which has been thus extended or
delayed by the above-mentioned time information
updating processing. Accordingly, it is possible to
avoid a situation, which would otherwise occur, in
which the relevant data would not arrive at the
15 transmission destination so that mismatch would
occur between the SystemClock in the decoding end
and the designated time information.

Accordingly, at the end of the MPEG
decoder 40, proper reproduction of video can be
20 executed immediately after the arrival of each frame
of the data stream through the network NW2. However,
as shown in FIG. 18, as a result of the above-
mentioned extension of the time information for each
frame due to the time information updating
25 processing, the reproduction speed is slowed down
accordingly.

FIG. 18 illustrates a change in video
reproduction state actually occurring in this case
as an example. As shown, an original (shown in FIG.
30 18, (a)) is a stream for reproducing image frames
with the interval of 33 msec. In case this stream
is coded into an MPEG stream in 6 Mbps as shown in
FIG.18, (b), reproduction of the image stream is
achieved in the same rate. However, when the time
35 information in the stream is extended according to
the triple band constriction into the narrow band of
2 Mbps as in the above-described first embodiment of

the present invention, the reproduction interval is extended thrice from 33 msec., which is same as that in the original, into 100 msec. when reproduction is executed according to the time information thus

5   updated and extended. As a result, the video reproduction speed becomes one third accordingly.

A coded data stream transmission system in a second embodiment of the present invention will now be described. In the system in the first

10   embodiment described above, the storage capacity of the MPEG stream buffer 33 in the MPEG transcoder 20 should have an increased size when the data amount received through the wide band network NW1 increases and data coded at a high bit rate should be

15   dispatched out through the narrow band network NW2. In other words, assuming a data transmission time period needed for transmitting data through the wide band network NW1 at a time of a specific event occurs as T, the data storage capacity size required

20   for the MPEG stream buffer 33 in the MPEG transcoder 20 is calculated by the following formula:

$$(RATE_B - RATE_N) \times T$$

25   That is, as the re-transmission is performed after the data transmission rate is reduced in the transcoder 20, a difference occurs between the data amount received from the MPEG encoder 10 and the data amount transmitted out through the narrow band

30   network NW2, and the data amount corresponding to this difference should be temporarily stored in the MPEG stream buffer 33.

Basically, the maximum data transmission time period through the wide band network NW1 at a

35   time of event occurrence should be determined such as to prevent the MPEG stream buffer 33 from overflowing during the period. However, the storage

capacity in the MPEG stream buffer 33 may not be
sufficient considering that an unexpected situation
may occur, i.e., for a case where data transmission
during a long time period is desired due to some
5   cause, for a case where a proper coordination
between a timing at which an event occurrence signal
is received externally and a timing of data
processing currently being executed in the
transcoder 20 cannot be achieved, or so. In such a
10   case, the MPEG transcoder 20 should discard/delete
the overflowing data amount to be processed for the
purpose of avoiding a worst result such as an
emergency shutdown or so.

          As being well-known, the MPEG stream is
15   formed of intra-frame coded image I pictures, inter-
frame forward-directional predictive coded image P
pictures and both-directional predictive coded image
B pictures. A group of pictures started by the I
picture is called a GOP (Group Of Picture).
20   Thereamoung, the I picture can be decoded alone,
while the top I picture in the GOP is needed for
decoding the other P pictures/B pictures in the GOP.

          As thus the I picture needs no surrounding
pictures for decoding it, a stream obtained from
25   thinning out of the P/B pictures provides a perfect
image quality by the I picture while frames of the
P/B pictures are omitted. Accordingly, the image
quality can be maintained at a time of reproduction
as for the frames of the I pictures. Thus,
30   according to the second embodiment, in addition to
the above-mentioned functional configuration of the
first embodiment, in case where the amount of data
stream which should be stored in the MPEG stream
buffer 33 becomes too large so that the data storage
35   capacity size is insufficient therefor, only the I
pictures are stored in the MPEG stream buffer 33 as
long as the capacity size in the MPEG streams buffer

33 is sufficient for storing only the I pictures
given. Furthermore, according to the second
embodiment, in case such a storage capacity
insufficiency situation becomes worth so that even
5   the I pictures cannot be stored in the MPEG stream
buffer 33, the entire GOP given is discarded.

The MPEG video packet includes a sequence
layer, a GOP layer, a picture layer, a slice layer,
a macro-block layer and a block layer. In the
10   picture layer, a PCT (Picture Coding Type) is
prepared indicating a picture type. By this
information, it is possible to determine whether a
given packet belongs to the I picture, the P picture
or the B picture.

15   FIG. 8 shows an operation flow chart
embodying the above-mentioned picture
discard/deletion processing in the transcoder 20
according to the second embodiment. With reference
thereto, an MPEG stream buffer management method in
20   the MPEG transcoder 20 according to the second
embodiment will be described. In the receiving
sequence in the MPEG transcoder 20 illustrated with
reference to FIG. 5, the picture discard sequence
shown in FIG. 8 is inserted immediately before the
25   operation of writing stream data into the MPEG
stream buffer 33.

First, in Step S31, it is determined
whether or not the received data of the MPEG stream
corresponds to the top of a GOP. In case where it
30   is the top of a GOP (Yes in Step S31), it is
determined in Step S32 where or not the remaining
storage capacity (available data storage amount) in
the buffer 33 is not less than a predetermined GOP
size. The predetermined GOP size is obtained, for
35   example, from multiplying the following value to the
coded bit rate in the MPEG encoder 10:

(the number of pictures included in one GOP) /
30

where approximately 30 pictures per second are
reproduced in a standard video reproduction process.

When the remaining storage capacity in the
MPEG stream buffer 33 is not less than the GOP size
(Yes), a predetermined deletion flag is set as "0"
(Step S33). In the other case (No), the remaining
storage capacity in the MPEG stream buffer is
compared with a predetermined VBV buffer size in
Step S34. The predetermined VBV buffer size is
previously set in the sequence layer in the MPEG
stream, and shows the maximum value of one picture.
In case where the remaining storage capacity in the
MPEG stream buffer 33 is not less than the VBV
buffer size (Yes), the deletion flag is set as "1"
in Step S35. In the other case (No), the deletion
flag is set as "2" in Step S36.
In case where the deletion flag is 0 (Yes
in Step S37), this means that at least one GOP can
be stored in the MPEG stream buffer 33. Accordingly,
the entire GOP given is written into the MPEG stream
buffer 33 in Step S41. when the deletion flag is 1
(No in Step S37 and also Yes in Step S38), this
means that only the I picture in the GOP can be
stored in the MPEG stream buffer 33. Accordingly,
only the I picture given is written thereto (in
Steps S39 and S41). When the deletion flag is 2 (No
in Step S38), this means that even one picture
cannot be stored in the MPEG stream buffer 33.
Accordingly, the entire GOP given is discarded in
Step S40. These operations (the loop of Steps S31
through S42) are repeated until the received data is
completed.
According to the above-described

processing according to the second embodiment of the present invention, even in a case where a proper coordination cannot be achieved between externally input even occurrence signal processing and current
5   data processing in the apparatus for example, the MPEG transcoding processing can be proceeded with without causing overflow in the MPEG stream buffer 33, and as a result, in the MPEG decoder 40 which receives data from the MPEG transcoder 20, it is
10 possible to reproduce video data without causing a serious error such as remarkable lacking in video images or so which would otherwise occur due to the overflow.

        A third embodiment of the present
15 invention will now be described. In the above-described first and second embodiments, it is assumed that the given MPEG stream includes only video data. However, according to the third embodiment, it is assumed that a given MPEG stream
20 may include both video data and audio data.

        Video data has a feature such that, even if a reproduction speed is slowed down to some extent, a human being can recognize the video contents without fail. On the other hand, in case
25 of audio data, when a reproduction speed is much slowed down, or intermittent reproduction is performed, a human being may not precisely recognize the contents thereof. Assuming that the present invention is applied to the accident monitoring
30 system as mentioned above or so, there may be a need such that at least a sound of the accident should be obtained in a cause where some accident occurs. Therefore, according to the third embodiment, audio data is dispatched from the transcoder 20
35 immediately after it is received there through the narrow band network NW2 in prior to dispatch of video data already stored in the MPEG stream buffer

33. Thereby, it is possible that reproduction of audio data is performed timely in a satisfactory condition in the receiving decoder 4.

According to the third embodiment, with regard to the above-mentioned processing, in the receiving processing in the transcoder 20, the received stream is stored in the MPEG stream buffer 33 in a manner such that the system header and video data are stored in the video buffer part included in the MPEG stream buffer while audio data is stored in the audio buffer part also included in the MPEG stream buffer 33 (see FIG. 5). In this regard, in each packet included in an MPEG stream, a stream ID (④ in FIG. 14) is prepared for determining whether the packet belongs to an MPEG video stream or an MPEG audio stream. By this information, it is possible to determine whether the given data is video data or audio data.

According to the third embodiment, in the transmission processing in the transcoder 20, upon occurrence of an event, when data exists in the audio buffer part of the MPEG stream buffer 33 (Yes in Step S12 of FIG. 6), the data in the audio buffer part of the MPEG stream buffer 33 is first dispatched out through the narrow band network NW2 in Steps S13 and S16. On the other hand, when no data exists in the audio buffer part in the MPEG stream buffer 33 (No in Step S12), data (video data or the system header) stored in the video buffer part of the MPEG stream buffer 33 is dispatched out through the narrow band network NW2 in Steps S14, S15 and S16 of FIG. 6. As mentioned above, audio data is requested to be dispatched as soon as possible so as to be reproduced in a real-time manner to the utmost extent in the receiving decoder 40. Accordingly, no updating is performed on the time information such as SCR values and PTS values

for the audio packets. In contrast thereto, as the
audio data is thus dispatched in prior to the video
data as mentioned above, the time information such
as the SCR values and PTS values thereof should be
5   shifted backward accordingly.

Specifically, assuming that the coded rate
in the audio data is $RATE_A$, the SCR value, PTS value
and DTS value in the MPEG stream of the video data
dispatched out through the narrow band network NW2
10   should be updated into those calculated by the
following formulas, respectively:

$$SCR_I + ((SCR_B - SCR_I) \times ((RATE_B + RATE_A)/RATE_N))$$

15   $$SCR_I + ((PTS_B - SCR_I) \times ((RATE_B + RATE_A)/RATE_N))$$

$$SCR_I + ((DTS_B - SCR_I) \times ((RATE_B + RATE_A)/RATE_N))$$

Furthermore, if one data transfer size
20   through the narrow ban network NW2 is too large,
dispatch processing through the narrow band network
NW2 should be delayed. In order to avoid such a
delay, it is needed to reduce one data transfer size
through the narrow band network NW2 with respect to
25   one data transfer size received through the wide
band network NW1, by the ratio between $RATE_N$ and
$RATE_B$, or more.

Thus, through the above-mentioned
processing in the third embodiment, it is possible
30   to reproduce the audio data in real-time manner in
the decoder 40 which receives the data stream
through the narrow band network NW2.

A fourth embodiment of the present
invention will now be described. In the above-
35   described first through third embodiments, proper
reproduction of received video and audio data is
achieved merely requiring a standard functional

configuration in the MPEG decoder 40 which receives
a data stream through the narrow band network NW2,
as a result of the time information in the MPEG
stream being appropriately updated in the MPEG
5   transcoder 20.

On the other hand, a user has a need to
again confirm the contents once reproduced already.
In order to respond to this request, stream storage
processing is needed also in the MPEG decoder 40.
10   However, if the MPEG stream buffer provided in the
MPEG decoder 40 stores therein the MPEG stream
having the time information extended and updated as
mentioned above, as it is, video reproduction speed
is also slowed down in case of again reproducing the
15   thus-stored contents according to the thus-extended
time information also in this case unnecessarily.
The fourth embodiment has been devised so as to
solve this issue. According to the fourth
embodiment, the MPEG stream thus once stored in the
20   decoder 40 in the state in which the time
information is extended and updated is again updated
to one with which the contents can be reproduced at
a real speed.

FIG. 9 shows a receiving sequence in the
25   MPEG decoder 40 according to the fourth embodiment.
With reference thereto, an MPEG stream storage
processing method in the MPEG decoder connected with
the narrowband network according to the fourth
embodiment will now be described.
30   First, in case where an MPEG stream
received through the narrow band network NW2 is of
an audio packet (in Step S51 and Yes in Step S52),
as the MPEG transcoder 20 which is the transmission
source of this MPEG stream has then not updated the
35   time information of this stream since it is the
audio packet as mentioned above, this received
stream is written into the stream buffer 44 as it is

in Step S53. On the other hand, when the received
MPEG stream is other than an audio packet (No in
Step S52), the time information thereof has been
updated in the MPEG transcoder acting as the
5   transmission source, and thus, the time information
updating part 52 in the decoder 40 should perform
time information restoration processing for the
received MPEG stream in Step S54.

Specifically, the first SCR is stored as
10   SCR_I. Then, in the other case, the SCR values, PTS
values and DTS values in the received MPEG stream
are replaced by the values calculated by the
following formulas, respectively, assuming that the
original SCR value, PTS value and DTS value are SCR_N,
15   PTS_N and DTS_n, respectively, the coded rate in the
data other than the audio data encoded in the MPEG
encoder 10 initially is $RATE_B$, the coded rate in the
audio data encoded in the MPEG encoder 10 initially
is $RATE_A$, and the circuit transfer rate in the
20   narrow band network NW2 is $RATE_N$:

$$SCR_I + ((SCR_N - SCR_I) \times (RATE_N/(RATE_B + RATE_A)))$$

$$SCR_I + ((PTS_N - SCR_I) \times (RATE_N/(RATE_B + RATE_A)))$$

25

$$SCR_I + ((DTS_N - SCR_I) \times (RATE_N/(RATE_B + RATE_A)))$$

That is, as a result of this time information
restoration processing, the respective time
30   information, i.e., SCR, PTS and DTS are returned to
ones same as those occurring before they are updated
in the MPEG transcoder 20.

Next, when an audio packet is stored in an
audio buffer part of the MPEG stream buffer 44, the
35   SCR value in the data of the received MPEG stream
updated or restored as mentioned above and the SCR
value in the audio packet stored at the top of the

audio buffer part of the MPEG stream buffer 44 are
compared with one another in Step S55. When it is
determined that the SCR value in the audio packet
stored indicates an earlier time (Yes), the audio
5   packet stored at the top in the audio buffer of the
MPEG stream buffer 44 is read out therefrom and
written into a video buffer part of the MPEG stream
buffer 44 in Step S56. After that, the relevant
data of the received MPEG stream is also written
10   into the video buffer part of the MPEG stream buffer
44 in Step S57. In the other case (No in Step S55),
Step S56 is skipped over, and thus, the relevant
data of the received MPEG stream is written into the
video buffer part of the MPEG stream buffer 44 in
15   Step S57. Thus, according to the SCR values
returned to the time information same as those
before they are updated in the MPEG transcoder 20,
the order of data is changed (re-arranged)
appropriately, and the data including the audio data
20   and video data are written into the video buffer of
the MPEG stream buffer 44 in the proper temporal
order so that video information and audio
information can be reproduced simultaneously by
reading out the data from the video buffer part of
25   the MPEG stream buffer 44.
        Thus, according to the processing
according to the fourth embodiment, in the MPEG
stream buffer 44 in the MPEG decoder 40, the same
stream as that initially dispatched by the MPEG
30   encoder 10 is stored finally. Accordingly, it is
possible to obtain a reproduction thereof in a
normal condition in case of reproducing the once
stored stream for the purpose of confirmation or so.
In the above description, an example where the
35   processing is performed during receiving the data
stream through the network has been mentioned.
However, it is not necessary to be limited to this

example. For another example, it is possible that
the transmitted stream is once received, and then,
after that, it is read out, and the above-described
time information restoration processing and data re-
5   arrangement (ordering change) processing are
performed.

A fifth embodiment according to the
present invention will now be described. In the
above-described first through fourth embodiments, a
10   received stream can be reproduced with a high image
quality with a minimum delay. There, even in a case
where a large size of data is received through a
narrow band network, it is not necessary to wait for
a completion of the entire stream nor to thinning
15   out video frames before dispatch. However, in these
embodiments, once encoded MPEG stream is dispatched
through a narrow band network providing a data
transfer rate lower than the originally coded rate.
Thereby, video reproduced in the decoder 40 is one
20   in which a delay increases gradually, as shown in
FIG. 18, (c), for example. In consideration of this
issue, the fifth embodiment has been devised.
According to the fifth embodiment, a user transmits,
via the transcoder 40, a reproduction time
25   designating request to the transcoder 20, and
thereby, enables dispatch of a part of a MPEG stream
having a desired time.

According to the fifth embodiment, a
designated reproduction time designated by the user
30   is defined as a time interval T_R (secs) measured
from a just event occurrence occasion, where:

$$0 \leq T_R \leq T_C$$

35   where T_C denotes a time interval between the event
occurrence occasion and the current time. This
designated reproduction time is requested by the

user who performs a monitoring work with a use of the MPEG decoder 40 for a predetermined event, for example.

The requested designated reproduction time is sent out toward the transcoder 20 via the request transmitting part 43 from the user IF part 41 in the decoder 40. In the MPEG transcoder 20, the designated reproduction time T_R is received via the request receiving part 28 from the MPEG decoder 40. There is a possibility that data relevant to the thus-requested time has been already transmitted from the transcoder 20. Accordingly, it is assumed that the MPEG stream even having been dispatched out should be left in the MPEG stream buffer 33 without being discarded. Thus, according to the fifth embodiment, the required size of the MPEG stream buffer 33 in the MPEG transcoder 20 is calculated by the following formula in case a data transmission time period through the wide band network NW1 at a time of the event occurrence is T:

$$RATE_B \times T$$

In the transcoder 20, the following processing is performed. It is assumed that the first SCR value occurring after the event occurs is SCR_I. Here, it is assumed that the SCR value is expressed by a constantly counted up value corresponding 90 kHz, i.e., it is a value counted up 90,000 times per one second. The SCR values for the pack headers set in the system headers stored in the MPEG stream buffer 33 are searched for the SCR value which differs from the above-mentioned SCR_I by not less than $90,000 \times T_R$. The thus obtained SCR value is stored as SCR_J. Then, the data in the MPEG stream buffer 33 having the SCR values later than the SCR_J are dispatched toward the MPEG decoder 40

in sequence. The respective time information, i.e.,
SCR value, PTS value and DTS value in the data
stream thus dispatched in this case are updated by
the values by the time information updating part 34
5   in the transcoder 20 calculated by the following
formulas:

$$SCR_J + ((SCR_B - SCR_J) \times (RATE_B/RATE_N))$$

10          $$SCR_J + ((PTS_B - SCR_J) \times (RATE_B/RATE_N))$$

$$SCR_J + ((DTS_B - SCR_J) \times (RATE_B/RATE_N))$$

The processing other than the above-described
15   processing performed in the transcoder 20 is same as
that in the above-described third embodiment.
According to the processing in the fifth
embodiment, a user can control data which should be
currently dispatched into data having a time which
20   is advanced from that of the data currently being
displaced or which is delayed from that of the data
currently being dispatched, according to the user's
desire. Accordingly, when an accumulated delay
amount, occurring due to gradually increasing delay
25   mentioned above with reference to FIG. 18, (c),
increases to some extent, the user may advance the
time of data to be currently dispatched (by
designating the above-mentioned designated
reproduction time interval T_R) so that the
30   accumulated delay may be cancelled. This operation
of advancing the time of data to be currently
dispatched means to skip several frames which belong
to the earlier or old timing. Then, if the user
feels that the above-mentioned operation of skipping
35   several frames belonging to the old timing has been
performed too much, the user may return the time of
data to be currently dispatched backward in time (by

designating the above-mentioned designated reproduction time interval T_R shorter) so that frames in older timing may be reproduced. Thus, the user can see video in the most desirable time zone.

5 Thus, according to the present invention, in a transcoder for receiving a MPEG stream through a wide band network and transmitting it through a narrow band network, time information given to the MPEG stream is changed according to a transmission

10 band width of a communication network applied for the transmission. Thereby, it is possible to dispatch the video contents transmitted in a state of high image quality with a reduced delay (without waiting for the completion of receiving the entire

15 large sized data), also, without needing thinning out of frames before dispatch, through the narrow band network. As a result, in a receiving apparatus which then receives the data through the narrow band network, it is possible to start seeing the video

20 contents simultaneously with the just time at which it is transmitted from the transmission source. Also, it is possible to receive all the frames and reproduce them. Thereby, even in a case where a plurality of video sources (encoders) exist

25 simultaneously, a user can see the contents of each video source in sequence, without waiting for a completion of receiving the entire data stream from each video source, and then can terminate the reception from one video source to move to another

30 video source rapidly thereamoung. Thus, the user can soon reach a certain video source which the user finally desires, and then, receive and reproduce the contents therefrom.

Furthermore, if an accumulated video delay

35 time increases to much, it is possible to bring the latest video to be reproduced according to a user's request. Further, it is also possible to return

backward to old frames for the purpose of confirmation or so. Thus, fine reproduction video time selection control can be achieved.

The present invention is not limited to the above-described embodiments, and variations and modifications may be made without departing from the claimed scope of the present invention.

The present application is based on Japanese priority application No. 2003-076336, filed on March 19, 2003, the entire contents of which are hereby incorporated by reference.